

INTERNATIONAL STANDARD



**Lead-acid starter batteries –
Part 2: Dimensions of batteries and dimensions and marking of terminals**

IECNORM.COM : Click to view the full PDF of IEC 60095-2:2021



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2021 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC online collection - oc.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 18 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IECNORM.COM : Click to view the full PDF IEC 60952:2021

INTERNATIONAL STANDARD



Lead-acid starter batteries – Part 2: Dimensions of batteries and dimensions and marking of terminals

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.220.20; 43.040.10

ISBN 978-2-8323-0000-8

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	5
1 Scope.....	7
2 Normative references	7
3 Terms and definitions	7
4 General requirements	8
4.1 General.....	8
4.2 Marking.....	8
4.2.1 Safety labelling.....	8
4.2.2 Marking of the polarity of terminals	8
4.3 Recycling	9
4.3.1 Recycling of lead	9
4.3.2 Recycling of plastic material	9
4.4 Dimensions and design	9
4.5 Dimensions of tapered battery terminals	9
5 Recommended types used in Europe (EU).....	10
5.1 General.....	10
5.2 Main dimensions of batteries.....	10
5.3 Handles	14
5.3.1 General	14
5.3.2 Mounting of handles	14
5.4 Mounting of batteries	15
5.4.1 General	15
5.4.2 Dimensions and arrangement of ledges and notches	15
5.5 Terminals.....	16
5.5.1 Position of terminals	16
5.5.2 Dimensions of battery terminals.....	16
5.5.3 Marking of polarity	16
5.6 Special features of the battery lid.....	17
5.6.1 General.....	17
5.6.2 Semi bloc lid.....	17
5.6.3 Central degassing.....	17
5.6.4 Recessed holes	17
5.6.5 Removable cell plugs.....	18
5.6.6 Position of sensor openings.....	18
5.7 Handling of starter batteries by robot-equipment.....	19
5.8 Bulging and reinforcement of battery side walls	21
6 Other battery types used in Europe (EU)	22
6.1 General.....	22
6.2 Main dimensions of batteries.....	23
6.3 Handles	28
6.4 Mounting of batteries	28
6.4.1 General	28
6.4.2 Dimensions and arrangement of ledges and notches	28
6.5 Terminals.....	28
6.5.1 Position of terminals	28
6.5.2 Dimensions of battery terminals.....	28

6.5.3	Marking of polarity	28
6.6	Handling of starter batteries by robot-equipment	28
7	Recommended types used in North America (AM)	31
7.1	General.....	31
7.2	Terminals and terminal configuration	31
7.2.1	Tapered terminals.....	31
7.2.2	Side terminals.....	31
7.2.3	Terminal configuration	32
7.3	Standard fastening on the bottom	32
7.3.1	General	32
7.3.2	Design of ledges.....	32
7.3.3	Design of recesses	33
7.4	Main dimensions of the battery group sizes AM.....	37
8	Recommended types used in East Asia (AS)	42
8.1	General.....	42
8.2	Terminals and terminal configuration	42
8.2.1	Design of terminals.....	42
8.2.2	Dimensions and classification of terminals.....	42
8.2.3	Configuration of terminals.....	42
8.3	Main dimensions of the battery group sizes AS.....	42
Figure 1	– Marking of polarity	8
Figure 2	– Marking of polypropylene-polyethylene copolymer battery components	9
Figure 3	– Dimensions of positive (on the right) and negative (on the left) terminal	10
Figure 4	– Main dimensions of batteries of standard series LN and LBN – Top view	11
Figure 5	– Details of Figure 4.....	12
Figure 6	– Main dimensions of batteries of standard series LN – Front view	13
Figure 7	– Main dimensions of batteries of standard series LN – Side view.....	14
Figure 8	– Details of ledges of Figure 6 and Figure 7	16
Figure 9	– Detail X – Notch on ledge.....	16
Figure 10	– Degassing outlet	17
Figure 11	– Recessed holes "M" for optional terminal protection	18
Figure 12	– Removable cell plugs and sensor positions	19
Figure 13	– Grips for handling by robot equipment.....	20
Figure 14	– Section P-P of Figure 13 and Figure 22.....	20
Figure 15	– Detail U of Figure 13 and Figure 22.....	21
Figure 16	– Maximum allowed bulging on short sides.....	21
Figure 17	– Reinforcement by thicker walls on short sides	22
Figure 18	– Reinforcement by additional ribs on short sides.....	22
Figure 19	– Main dimensions of batteries of series L, LB, E, EB	26
Figure 20	– Main dimensions of batteries of series LS, LBS, ES, EBS	27
Figure 21	– Details of Figure 19 and Figure 20	27
Figure 22	– Grips for handling by robot equipment for LBN series.....	29
Figure 23	– Grips for handling by robot equipment for L and LS series	29
Figure 24	– Detail V of Figure 23	30

Figure 25 – Grips for handling by robot equipment for LB and LBS series – Option 1	30
Figure 26 – Grips for handling by robot equipment for LB and LBS series – Option 2	30
Figure 27 – Detail Y of Figure 25 and Figure 26	31
Figure 28 – Side terminal groove description	32
Figure 29 – Side terminal groove dimensions in mm and (in)	32
Figure 30 – Design for batteries with ledges on long sides for hold-down-devices in mm and (in)	33
Figure 31 – Design for batteries with recesses on long sides for hold-down-devices in mm and (in)	34
Figure 32 – Design for batteries with recesses on sides for hold-down-devices in mm and (in)	35
Figure 33 – Design for batteries with recesses on sides for hold-down-devices in mm and (in)	36
Figure 34 – Design for batteries with recesses on sides for hold-down-devices in mm and (in)	37
Figure 35 – Main dimensions of batteries of group sizes 24R, 26R, 34R, 35, 51R, 85	39
Figure 36 – Main dimensions of batteries of group size 24, 25, 26, 27, 34, 51, 86	39
Figure 37 – Main dimensions of batteries of group size 36R	40
Figure 38 – Main dimensions of batteries of group sizes 59, 65	40
Figure 39 – Main dimensions of batteries of group size 75, 78, 100 with positive terminal on the right	41
Figure 40 – Main dimensions of batteries of group size 75, 78, 100 with positive terminal on the left	41
Figure 41 – Main dimensions of battery group sizes AS	43
Table 1 – Main dimensions of batteries of standard series LN	11
Table 2 – Main dimensions of batteries of other series LBN	23
Table 3 – Main dimensions of other series L, LS, LB and LBS	24
Table 4 – Main dimensions of other series E, ES, EB and EBS	25
Table 5 – Battery group sizes AM	38
Table 6 – Dimensions and classification of terminals	42
Table 7 – Dimensions of group sizes AS	43

INTERNATIONAL ELECTROTECHNICAL COMMISSION

LEAD-ACID STARTER BATTERIES –**Part 2: Dimensions of batteries and
dimensions and marking of terminals****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60095-2 has been prepared by IEC technical committee 21: Secondary cells and batteries.

This fifth edition cancels and replaces the fourth edition published in 2009. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) update of the dimensions of batteries:
 - in Europe according to the last version of the European standard;
 - in USA with figures updated;
 - in Asia with one type of Japanese battery removed.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
21/1086/FDIS	21/1092/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 60095 series, published under the general title *Lead-acid starter batteries*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

LEAD-ACID STARTER BATTERIES –

Part 2: Dimensions of batteries and dimensions and marking of terminals

1 Scope

This part of IEC 60095 is applicable to lead-acid batteries used for starting, lighting and ignition of passenger cars and light vehicles with a nominal voltage of 12 V.

All batteries in accordance with this document can be fastened to the vehicle either by means of the ledges around the container or by means of a hold-down device engaging with the lid.

This document specifies dimensions of battery for Europe, East Asia and North America.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-482, *International Electrotechnical Vocabulary – Part 482: Primary and secondary cells and batteries*

IEC 60095-1:2018, *Lead-acid starter batteries – Part 1: General requirements and methods of test*

IEC 60417:2002, *Graphical symbols for use on equipment*

ISO/IEC 10646, *Information technology – Universal coded character set (UCS)*

ISO 1043-1, *Plastics – Symbols and abbreviated terms – Part 1: Basic polymers and their special characteristics*

ISO 11469, *Plastics – Generic identification and marking of plastics products*

3 Terms and definitions

For the purpose of this document, the terms and definitions given in IEC 60050-482 apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

4 General requirements

4.1 General

The specifications of Clause 4 are common to all starter batteries according to this document.

4.2 Marking

4.2.1 Safety labelling

The batteries shall bear the six coloured safety symbols in accordance with 6.1.6 of IEC 60095-1:2018.

4.2.2 Marking of the polarity of terminals

4.2.2.1 General

The batteries shall carry the marking of polarity, at least of the positive terminal.

4.2.2.2 Marking of positive terminals

This marking shall take the form of the symbol "+" either on the upper surface of the positive terminal or on the lid adjacent to the positive terminal.

4.2.2.3 Marking of negative terminals

This marking shall take the form of the symbol "-" either on the upper surface of the negative terminal or on the lid adjacent to the negative terminal.

4.2.2.4 Design and dimensions of marking of terminals

The symbols used for marking the terminals shall be in accordance with IEC 60417-5005:2012-10 for the positive and IEC 60417-5006:2012-10 for the negative polarity.

The dimensions of the marking shall be according to Figure 1.




Figure 1 – Marking of polarity

The polarity symbols may be either indented or embossed by $(0,4 \pm 0,1)$ mm.

As an alternative, the wordings "POS" and "NEG" are permitted for the North American market only.

4.3 Recycling

4.3.1 Recycling of lead

The batteries shall be marked with the symbols for recycling and separate collection according to IEC 60095-1.

4.3.2 Recycling of plastic material

Injection moulded battery components need to be marked according to ISO 11469 and ISO 1043-1. The marking shall be placed on the bottom of the battery container or on one short side near the ledge.

According to ISO 11469 and ISO 1043-1 the minimum marking for polypropylene-polyethylene copolymer is >PP< or >PP/PE<.

In addition it is possible to show the recycling symbol with number 7 (Unicode character 'RECYCLING SYMBOL FOR TYPE-7 PLASTICS' (U+2679) according to ISO/IEC 10646) and the term "Other".

The recommended thickness is $(0,3 \pm 0,1)$ mm. The height of the marking characters shall be between 3 mm and 7 mm.

An example for this marking is shown in Figure 2.



Figure 2 – Marking of polypropylene-polyethylene copolymer battery components

4.4 Dimensions and design

All dimensions given in this document correspond to a temperature of 20 °C of the polypropylene-polyethylene copolymer.


Details of the design that are not indicated in the generic drawings need to be chosen appropriately.

The generic drawings in this document are possible examples only. Especially the design of the lid, handles, ribs, ledges and vent caps are not mandatory in total.

4.5 Dimensions of tapered battery terminals

The dimensions of the tapered positive and negative terminal shall be according to Figure 3.

Dimensions in millimetres



IEC

Key

- 1 Edge with radius
- 2 Convex or concave surface design permitted within height dimensions of (18^{+1}_{-2}) mm related to the center of the terminal

Figure 3 – Dimensions of positive (on the right) and negative (on the left) terminal

5 Recommended types used in Europe (EU)

5.1 General

For new battery developments, only the recommended series shall be used.

Clause 5 specifies:

- the main dimensions of starter batteries of the preferred LN series;
- the location of the positive and negative terminals with respect to the fastening system;
- the dimensions of tapered terminals of starter batteries.

5.2 Main dimensions of batteries


The main dimensions of the batteries of the LN series are shown in Table 1 and Figure 4, Figure 5, Figure 6 and Figure 7.

NOTE The schematic drawings do not show every design detail of the battery.


The following symbols are used:

- | | |
|-------|--|
| a_1 | Overall length at the battery base with ledges |
| a_2 | Length at the battery base without ledges |
| a_3 | Length at battery lid |
| a_4 | Distance of the inside notches |
| a_5 | Distance between terminal and the edges of the lid at the short side (see Figure 4 and Figure 6) |
| a_6 | Distance of the grip-segments for handling by robot equipment (see Figure 14) |

Dimensions in millimetres



a) Detail K



b) Detail L


Key

- 1 Ledge on battery front side
- 2 Ledge on battery back side

Figure 5 – Details of Figure 4

IECNORM.COM : Click to view the full PDF of IEC 60095-2:2021

Dimensions in millimetres




IEC

Key

- 1 Negative terminal
- 2 Positive terminal
- 3 Handles shown as example only
- 4 Both versions acceptable
- 5 Interruption acceptable

Figure 6 – Main dimensions of batteries of standard series LN – Front view

Dimensions in millimetres



IEC

Key

- 1 Degassing outlet
- 2 Top clamp area
- 3 Top clamp area
- 4 Robotic grip
- 5 Ribs acceptable
- 6 Ledge
- 7 Notch
- 8 For flooded batteries
- 9 For VRLA batteries

Figure 7 – Main dimensions of batteries of standard series LN – Side view

5.3 Handles

5.3.1 General

Batteries with a weight less than or equal to 20 kg may be designed without, with one, or with two handles. Batteries with a weight of more than 20 kg shall have two handles.

5.3.2 Mounting of handles

If the batteries have handles, the handles shall be integrated in the lid (see Figure 4).

NOTE The handle design shown on all the pages of this document is for information only. It is left to the battery manufacturer to propose a design in accordance with this document with respect to overall dimensions.

5.4 Mounting of batteries

5.4.1 General

Starter batteries in accordance with the LN series may be fixed to the vehicles either:

- by a bottom hold-down device of the long side,
- by a bottom hold-down device of the short side, or
- by means of a hold-down device engaging with the upper part of the battery (for example, a metal frame), connected to the top clamping area (see Figure 4 and Figure 7).

In either case, these batteries shall have top clamping areas on the long sides.

The hold-down clamps of support shall match with the ledges and notches to provide secure fastening in all directions.

5.4.2 Dimensions and arrangement of ledges and notches

All batteries of the LN series shall have ledges for fastening over the length of all sides as an integral part of the battery container and allowing the battery to be fixed by means of the bottom of the container.


The positions and dimensions of ledges and notches shall be according to Figure 6 and Figure 7.

The profile of the ledges shall be in accordance with Figure 8 and Figure 9. The length of the ledges on the rear side of the battery shall be reduced by 20 mm from both ends compared to the one on the front side (see Figure 4).


The hold-down clamps of the support shall match with the ledges and the notches to provide secure fastening in either direction.

To allow a symmetrical rotation for fastening the opposite ledges contain an equal number of notches. To secure correct positioning of the battery on the support the ledges shall have 5 notches on the long sides and 3 notches on the short sides.

Dimensions in millimetres



IEC




IEC

a) Details of section M-M –
Ledge on the long sides

b) Details of section N-N –
Ledge on the short side

Figure 8 – Details of ledges of Figure 6 and Figure 7

Dimensions in millimetres



IEC

Figure 9 – Detail X – Notch on ledge

5.5 Terminals

5.5.1 Position of terminals

The position of positive and negative terminals shall be in accordance with Figure 4.

5.5.2 Dimensions of battery terminals

The dimensions of the tapered positive and negative terminal shall be according to Figure 3.

5.5.3 Marking of polarity

The polarity of the batteries of the LN series shall be marked twice in the area of the terminals (see Figure 4).

The symbol of the polarity and the dimension of the symbols shall be in accordance with 4.2.2.

5.6 Special features of the battery lid

5.6.1 General

Batteries of the LN series shall have the following details.

5.6.2 Semi bloc lid

Batteries of the LN series shall have a block lid which includes the terminals and the vent plugs so that they are not higher than the lid surface. A special feature of the semi bloc lid is the top clamping area (see Figure 4 and Figure 7).

5.6.3 Central degassing

Batteries of the LN series shall have a central degassing system with degassing outlets at one or both of the short sides (see Figure 7 and Figure 10).

The central degassing system shall be designed in such a way that charging gasses from all six cells can leave the battery via all available outlets. A separation of a subset of cells to one outlet is not permissible.

A minimum depth of 10 mm for the insertion of connection parts in the degassing outlet shall be provided.

Any connection parts shall be connected gas tight to the degassing outlet.

Dimensions in millimetres





Figure 10 – Degassing outlet

5.6.4 Recessed holes

Batteries of the LN series shall have recessed holes 'M' for optional terminal protection covers on both sides (see Figure 4 and Figure 11).

Dimensions in millimetres



Key

1 optional

Figure 11 – Recessed holes "M" for optional terminal protection


5.6.5 Removable cell plugs

If removable cell plugs are used in batteries of the LN series a flat battery surface shall be maintained and their position shall be according to Figure 12.

5.6.6 Position of sensor openings

Optional sensor openings of batteries of the LN series might be placed in one of the cell openings (V) or separate sensor openings (S). The sensor openings shall have the diameter and position according to Figure 12 and Table 1.

Dimensions in millimetres



IEC


Key

- V Cell openings for removable cell plugs or optional sensors
- S Additional optional sensor openings
- A Dimension defined in Table 1
- B Dimension defined in Table 1

Figure 12 – Removable cell plugs and sensor positions**5.7 Handling of starter batteries by robot-equipment**

Optional grips for the handling of LN series batteries by robot-equipment shall comply with Figure 13, Figure 14, Figure 15 and Table 1.


Dimensions in millimetres



Key

- 1 Both versions acceptable
- 2 Interruption acceptable

Figure 13 – Grips for handling by robot equipment



Key

- 1 Wall reinforcement in this area acceptable

Figure 14 – Section P-P of Figure 13 and Figure 22

Dimensions in millimetres




Figure 15 – Detail U of Figure 13 and Figure 22

5.8 Bulging and reinforcement of battery side walls

The maximum bulging of battery side walls shall not exceed the maximum tolerance of 5 mm as shown in Figure 16. In addition the maximum bulging shall not exceed 2 mm at 30 mm height.

All dimensions refer to new batteries at the start of electrical testing according to IEC 60095-1 and not to aged batteries.

Reinforced side walls may be needed for certain types of starter batteries (e.g. VRLA batteries) to prevent excessive bulging. This can be realized by means of thicker side walls or additional ribs as shown in Figure 17 and Figure 18.

Dimensions in millimetres




Figure 16 – Maximum allowed bulging on short sides





Figure 17 – Reinforcement by thicker walls on short sides



Key

- 1 Ribs shown as example only

Figure 18 – Reinforcement by additional ribs on short sides

6 Other battery types used in Europe (EU)

6.1 General

Clause 6 applies to types of lead-acid starter batteries for passenger cars and light vehicles widely and predominantly used in Europe. In the following, the series is designated "EU".

The following battery types are listed for reference only and shall not be used for new developments.

The object of this clause is to specify:

- the main dimensions of starter batteries of LBN, L, LB, E, EB, LS, LBS, ES and EBS series;
- the location of the positive and negative terminals with respect to the fastening system;
- the dimensions of tapered terminals;
- the marking of the polarity.

6.2 Main dimensions of batteries

The main dimensions of the batteries of series LBN are shown in Table 2, Figure 4, Figure 5, Figure 6 and Figure 7. Note that the main difference of LBN types compared to LN types is the dimensions H and h .

The main dimensions of the batteries of series L, LS, LB and LBS are shown in Table 3, Figure 19, Figure 20 and Figure 21.

The main dimensions of the batteries of series E, ES, EB and EBS are shown in Table 4, Figure 19, Figure 20 and Figure 21.

NOTE The schematic drawings do not show every design detail of the battery.

The following symbols are used:

- b Overall width above ledges
- b_1 Width across ledges
- l Overall length without handles
- l_1 Length at battery base
- l_2 Length at battery base with ledges
- C Additional length for handles
- H Overall height including lid, plugs and terminals

Table 2 – Main dimensions of batteries of other series LBN

Dimensions in millimetres

Type	a_1	a_2	a_3	a_4	a_5	A	B	H	h
	+0 / -2	± 1	+0 / -3	+0 / -1	± 2	± 2	± 2	+0 / -3	+0 / -4
LBN 0	175	161	175	40	19	13	40	175	153
LBN 1	207	193	207	40	24	18	48		
LBN 2	242	228	242	40	26	19	57		
LBN 3	278	264	277	40	29	27	65		
LBN 4	315	301	314	40	31	27	74		
LBN 5	353	339	352	60	27	28	84		
LBN 6	394	379	393	60	30	31	94		

Table 3 – Main dimensions of other series L, LS, LB and LBS

Dimensions in millimetres


Series	Type	Length			Width		Height		Grips	Handles
		l	l_1 max	l_2	b +0 / -4	b_1 +0 / -2	H +0 / -4	h +0 / -4	a ± 2	C max
L	L 0	175 ⁺⁰ ₋₂	162	-	175	175 ⁺⁰ ₋₂	190	169	-	14
	L 1	207 ⁺⁰ ₋₂	194	-					95	
	L 2	242 ⁺⁰ ₋₂	229	-					113	
	L 3	278 ⁺⁰ ₋₃	265	-					130	
	L 4	315 ⁺⁰ ₋₃	302	-					150	
	L 5	353 ⁺⁰ ₋₄	340	-					168	
LS	LS 1	207 ⁺⁰ ₋₂	194	207 ⁺⁰ ₋₂	175	175 ⁺⁰ ₋₂	190	169	95	14
	LS 2	242 ⁺⁰ ₋₂	229	242 ⁺⁰ ₋₂					113	
	LS 3	278 ⁺⁰ ₋₃	265	278 ⁺⁰ ₋₃					130	
	LS 4	315 ⁺⁰ ₋₃	302	315 ⁺⁰ ₋₃					150	
	LS 5	353 ⁺⁰ ₋₄	340	353 ⁺⁰ ₋₄					168	
LB	LB 1	207 ⁺⁰ ₋₂	194	-	175	175 ⁺⁰ ₋₂	175	154	95	14
	LB 2	242 ⁺⁰ ₋₂	229	-					113	
	LB 3	278 ⁺⁰ ₋₃	265	-					130	
LBS	LBS 1	207 ⁺⁰ ₋₂	194	207 ⁺⁰ ₋₂	175	175 ⁺⁰ ₋₂	175	154	95	14
	LBS 2	242 ⁺⁰ ₋₂	229	242 ⁺⁰ ₋₂					113	
	LBS 3	278 ⁺⁰ ₋₃	265	278 ⁺⁰ ₋₃					130	

Table 4 – Main dimensions of other series E, ES, EB and EBS

Dimensions in millimetres

Series	Type	Length			Width		Height		Handles
		l	l_1 max	l_2	b +0 / -4	b_1	H +0 / -4	h +0 / -4	C max
E	E1	178 ⁺⁰ ₋₂	173	-	135	135 ⁺⁰ ₋₂	225	204	14
	E2	219 ⁺⁰ ₋₂	214	-					
	E3	260 ⁺⁰ ₋₃	255	-					
	E4	301 ⁺⁰ ₋₃	296	-					
ES	ES 1	178 ⁺⁰ ₋₂	173	186 ⁺⁰ ₋₂	135	135 ⁺⁰ ₋₂	225	204	14
	ES 2	219 ⁺⁰ ₋₂	214	227 ⁺⁰ ₋₂					
	ES 3	260 ⁺⁰ ₋₃	255	268 ⁺⁰ ₋₃					
	ES 4	301 ⁺⁰ ₋₃	296	309 ⁺⁰ ₋₃					
EB	EB 1	178 ⁺⁰ ₋₄	174	-	135	135 ⁺⁰ ₋₄	205	185	14
	EB 2	220 ⁺⁰ ₋₄	216	-					
	EB 3	266 ⁺⁰ ₋₅	262	-					
	EB 4	315 ⁺⁰ ₋₅	311	-					
EBS	EBS 1	178 ⁺⁰ ₋₄	174	188 ⁺⁰ ₋₂	135	135 ⁺⁰ ₋₄	205	185	14
	EBS 2	220 ⁺⁰ ₋₄	216	230 ⁺⁰ ₋₂					
	EBS 3	266 ⁺⁰ ₋₅	262	276 ⁺⁰ ₋₃					
	EBS 4	315 ⁺⁰ ₋₅	311	326 ⁺⁰ ₋₄					

Dimensions in millimetres




Key

- 1 Notch
- 2 Ledge

Figure 19 – Main dimensions of batteries of series L, LB, E, EB

Dimensions in millimetres




IEC

Key

- 1 Notch
- 2 Ledge

Figure 20 – Main dimensions of batteries of series LS, LBS, ES, EBS

Dimensions in millimetres

**a) Details X of Figure 19 and Figure 20****b) Sections R and T of Figure 19 and Figure 20****Figure 21 – Details of Figure 19 and Figure 20**

6.3 Handles

Batteries in accordance with this document may have handles. The projection 'C' of handles (see Figure 19, Figure 20 or Figure 21) shall not exceed the values given in Table 3 and Table 4. The handles shall be capable of being folded or removed so as not to interfere with the other dimensions.

6.4 Mounting of batteries

6.4.1 General

Starter batteries in accordance with this document may be fixed to the vehicles either:

- by a bottom hold-down device of the long side (L, LB, E, EB series),
- by a bottom hold-down device of the short side (LS, LBS, ES, EBS series), or
- by means of a hold-down device engaging with the upper part of the battery (for example, a metal frame).

6.4.2 Dimensions and arrangement of ledges and notches

All batteries in accordance with this document shall have ledges (or recesses forming ledges) over the full length of the long sides of the container. The ledges shall be an integral part of the battery container and allow the battery to be fixed by means of the bottom of the container.

The position and dimensions of ledges and notches shall be according to Figure 19, Figure 20 and Figure 21.

The hold-down clamps of support shall match with the ledges and notches to provide secure fastening in all directions.

The hold-down clamps of the support shall match with the ledges and the notches to provide secure fastening in either direction.

To secure correct positioning of the battery on the support, the ledge on the side of the terminals shall have one notch; the ledge on the opposite side shall have two notches. Three or five notches on both sides are permitted.

6.5 Terminals

6.5.1 Position of terminals

The position of positive and negative terminal shall be in accordance with Figure 19, Figure 20 or Figure 21.

6.5.2 Dimensions of battery terminals

The dimensions of the tapered positive and negative terminal shall be in accordance with Figure 3.

6.5.3 Marking of polarity

The polarity of the batteries shall be marked in accordance with 4.2.2 at least for the positive terminal.

If the negative terminal is also marked, the symbol used shall also be in accordance with 4.2.2.

6.6 Handling of starter batteries by robot-equipment

Optional grips for handling of LBN series batteries shall comply with Figure 22.

Optional grips for handling of L and LS series batteries by robot-equipment shall comply with Figure 23.

Optional grips for handling of LB and LBS series batteries by robot-equipment shall comply with Figure 25 or Figure 26.

Robot grips shall not exceed dimensions of the lid (see detail V according to Figure 24 and detail Y according to Figure 27).




Figure 22 – Grips for handling by robot equipment for LBN series




Figure 23 – Grips for handling by robot equipment for L and LS series

Dimensions in millimetres




Figure 24 – Detail V of Figure 23

Dimensions in millimetres




Figure 25 – Grips for handling by robot equipment for LB and LBS series – Option 1

Dimensions in millimetres




Figure 26 – Grips for handling by robot equipment for LB and LBS series – Option 2

Dimensions in millimetres




Figure 27 – Detail Y of Figure 25 and Figure 26

7 Recommended types used in North America (AM)

7.1 General

Clause 7 applies to types of lead-acid starter batteries for passenger cars and light vehicles widely and predominantly used in North America. In the following, the group sizes are designated "AM". The group sizes AM comprise 19 types of batteries. They cover the majority of present aftermarket need. All of 19 types are designed to be fastened to the vehicle by means of ledges on the long sides of the battery container which are, however, different from those specified in Clause 5 and Clause 6.

7.2 Terminals and terminal configuration


7.2.1 Tapered terminals

The dimensions of the tapered positive and negative terminal shall be according to Figure 3.

7.2.2 Side terminals

Two types of these group sizes AM have side terminals in accordance with Figure 28 and Figure 29.

IMPORTANT: Battery types with side terminals are not recommended types for new developments.



NOTE 1 “3/8 – 16 UNC-2B” is according to ANSI ASME B.1.1.

NOTE 2 Dimension are given in millimetres and, in brackets, in inches.

Figure 28 – Side terminal groove description

Dimensions in millimetres and in brackets, in inches




Figure 29 – Side terminal groove dimensions in mm and (in)

7.2.3 Terminal configuration

The terminal configurations are shown in Figure 35 through Figure 40. Dimensions are given in Table 5.

7.3 Standard fastening on the bottom

7.3.1 General

All batteries of these group sizes AM shall have ledges or recesses for fastening over the length or over the front as an integral part of the battery container and allowing the battery to be fixed by means of the bottom of the container.

7.3.2 Design of ledges

The profile of the ledges shall be in accordance with Figure 30.

Dimensions in millimetres and in brackets, in inches





Figure 30 – Design for batteries with ledges on long sides for hold-down-devices in mm and (in)

7.3.3 Design of recesses

The profile of the recesses shall be in accordance with Figure 31, Figure 32, Figure 33 and Figure 34.

Dimensions in millimetres and in brackets, in inches



IEC

Figure 31 – Design for batteries with recesses on long sides for hold-down-devices in mm and (in)

Dimensions in millimetres and in brackets, in inches





Figure 32 – Design for batteries with recesses on sides for hold-down-devices in mm and (in)

Dimensions in millimetres and in brackets, in inches



IEC

Figure 33 – Design for batteries with recesses on sides for hold-down-devices in mm and (in)