

INTERNATIONAL
STANDARD

ISO/IEC/
IEEE
8802-1Q

First edition
2016-03-15

AMENDMENT 4
2017-11

**Information technology —
Telecommunications and information
exchange between systems — Local
and metropolitan area networks —
Specific requirements —**

**Part 1Q:
Bridges and bridged networks**

AMENDMENT 4: Frame preemption

*Technologies de l'information — Télécommunications et échange
d'information entre systèmes — Réseaux locaux et métropolitains —
Exigences spécifiques —*

Partie 1Q: Ponts et réseaux pontés

AMENDEMENT 4: Prémption de trame



Reference number
ISO/IEC/IEEE 8802-1Q:2016/Amd.4:2017(E)

© IEEE 2016



COPYRIGHT PROTECTED DOCUMENT

© IEEE 2016

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO or IEEE at the address below or ISO's member body in the country of the requester.

ISO copyright office
Ch. de Blandonnet 8 • CP 401
CH-1214 Vernier, Geneva, Switzerland
Tel. +41 22 749 01 11
Fax +41 22 749 09 47
copyright@iso.org
www.iso.org

Institute of Electrical and Electronics Engineers, Inc
3 Park Avenue, New York
NY 10016-5997, USA

stds.ipr@ieee.org
www.ieee.org

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE-SA) Standards Board. The IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and serve without compensation. While the IEEE administers the process and establishes rules to promote fairness in the consensus development process, the IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards.

The main task of ISO/IEC JTC 1 is to prepare International Standards. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is called to the possibility that implementation of this standard may require the use of subject matter covered by patent rights. By publication of this standard, no position is taken with respect to the existence or validity of any patent rights in connection therewith. ISO/IEEE is not responsible for identifying essential patents or patent claims for which a license may be required, for conducting inquiries into the legal validity or scope of patents or patent claims or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance or a Patent Statement and Licensing Declaration Form, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from ISO or the IEEE Standards Association.

ISO/IEC/IEEE 8802-1Q:2016/Amd.4 was prepared by the LAN/MAN of the IEEE Computer Society (as IEEE STD 802.1Qb-2014). It was adopted by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 6, *Telecommunications and information exchange between systems*, in parallel with its approval by the ISO/IEC national bodies, under the “fast-track procedure” defined in the Partner Standards Development Organization cooperation agreement between ISO and IEEE. IEEE is responsible for the maintenance of this document with participation and input from ISO/IEC national bodies.

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC/IEEE 8802-1Q:2016/Amd 4:2017

IEEE Std 802.1Qbu™-2016
(Amendment to
IEEE Std 802.1Q™-2014)

**IEEE Standard for
Local and metropolitan area networks—**

Bridges and Bridged Networks— Amendment 26: Frame Preemption

Sponsor
**LAN/MAN Standards Committee
of the
IEEE Computer Society**

Approved 30 June 2016
IEEE-SA Standards Board

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC/IEEE 8802-1Q:2016/Amd 4:2017

Abstract: Enhancements to the forwarding process that support frame preemption are provided in this amendment to IEEE Std 802.1Q-2014.

Keywords: Bridged Local Area Networks, IEEE 802.1Q™, LANs, local area networks, MAC Bridges, metropolitan area networks, preemption, Virtual Bridged Local Area Networks, virtual LANs

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2016 by the Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 30 August 2016. Printed in the United States of America.

IEEE and 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by the Institute of Electrical and Electronics Engineers, Incorporated.

PDF: ISBN 978-1-5044-2257-4 STD21074
Print: ISBN 978-1-5044-2258-1 STDPD21074

IEEE prohibits discrimination, harassment, and bullying. For more information, visit <http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html>.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page, appear in all standards and may be found under the heading “Important Notice” or “Important Notices and Disclaimers Concerning IEEE Standards Documents.”

Notice and Disclaimer of Liability Concerning the Use of IEEE Standards Documents

IEEE Standards documents (standards, recommended practices, and guides), both full-use and trial-use, are developed within IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (“IEEE-SA”) Standards Board. IEEE (“the Institute”) develops its standards through a consensus development process, approved by the American National Standards Institute (“ANSI”), which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE does not warrant or represent the accuracy or content of the material contained in its standards, and expressly disclaims all warranties (express, implied and statutory) not included in this or any other document relating to the standard, including, but not limited to, the warranties of: merchantability; fitness for a particular purpose; non-infringement; and quality, accuracy, effectiveness, currency, or completeness of material. In addition, IEEE disclaims any and all conditions relating to: results; and workmanlike effort. IEEE standards documents are supplied “AS IS” and “WITH ALL FAULTS.”

Use of an IEEE standard is wholly voluntary. The existence of an IEEE standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE should be considered the approved IEEE standard.

Official statements

A statement, written or oral, that is not processed in accordance with the IEEE-SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, or be relied upon as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that his or her views should be considered the personal views of that individual rather than the formal position of IEEE.

Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE. However, IEEE does not provide consulting information or advice pertaining to IEEE Standards documents. Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its societies and Standards Coordinating Committees are not able to provide an instant response to comments or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in revisions to an IEEE standard is welcome to join the relevant IEEE working group.

Comments on standards should be submitted to the following address:

Secretary, IEEE-SA Standards Board
445 Hoes Lane
Piscataway, NJ 08854 USA

Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not imply compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

Copyrights

IEEE draft and approved standards are copyrighted by IEEE under U.S. and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

Photocopies

Subject to payment of the appropriate fee, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every ten years. When a document is more than ten years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit the IEEE-SA Website at <http://ieeexplore.ieee.org/browse/standards/collection/ieee> or contact IEEE at the address listed previously. For more information about the IEEE SA or IEEE's standards development process, visit the IEEE-SA Website at <http://standards.ieee.org>.

Errata

Errata, if any, for all IEEE standards can be accessed on the IEEE-SA Website at the following URL: <http://standards.ieee.org/findstds/errata/index.html>. Users are encouraged to check this URL for errata periodically.

Patents

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken by the IEEE with respect to the existence or validity of any patent rights in connection therewith. If a patent holder or patent applicant has filed a statement of assurance via an Accepted Letter of Assurance, then the statement is listed on the IEEE-SA Website at <http://standards.ieee.org/about/sasb/patcom/patents.html>. Letters of Assurance may indicate whether the Submitter is willing or unwilling to grant licenses under patent rights without compensation or under reasonable rates, with reasonable terms and conditions that are demonstrably free of any unfair discrimination to applicants desiring to obtain such licenses.

Essential Patent Claims may exist for which a Letter of Assurance has not been received. The IEEE is not responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patent Claims, or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from the IEEE Standards Association.

Participants

At the time this standard was completed, the IEEE 802.1 working group had the following membership:

Glenn Parsons, Chair
John Messenger, Vice-Chair
Michael Johas Teener, Chair, Time Sensitive Networking Task Group
Tony Jeffree, Editor

Christian Boiger	Stephan Kehrer	Jessy Rouyer
Paul Bottorff	Marcel Kiessling	Panagiotis Saltsidis
David Chen	Philippe Klein	Michael Seaman
Feng Chen	Jouni Korhonen	Daniel Sexton
Weiyang Cheng	Yizhou Li	Johannes Specht
Rodney Cummings	Christophe Mangin	Wilfried Steiner
Janos Farkas	Tom McBeath	Patricia Thaler
Norman Finn	James McIntosh	David Thornburg
Geoffrey Garner	Hiroki Nakano	Jeremy Touve
Eric Gray	Bob Noseworthy	Paul Unbehagen
Craig Gunther	Donald R. Pannell	Karl Weber
Stephen Haddock	Walter Pieniac	Brian Weis
Mark Hantel	Karen Randall	Jordon Woods
Marc Holness	Maximilian Riegel	Helge Zinner
Hal Keen	Dan Romascanu	Juan Carlos Zuniga

The following members of the individual balloting committee voted on this standard. Balloters may have voted for approval, disapproval, or abstention.

Thomas Alexander	Michael Johas Teener	Dan Romascanu
Butch Anton	Adri Jovin	Jessy Rouyer
Lee Armstrong	Shinkyo Kaku	Larry Samberg
Stefan Aust	Piotr Karocki	Bartien Sayogo
Christian Boiger	Stuart Kerry	Michael Seaman
Nancy Bravin	Yongbum Kim	David Solomon
William Byrd	Robert Landman	Kevin Stanton
Juan Carreon	Mark Laubach	Thomas Starai
Rodney Cummings	David Lewis	Eugene Stoudenmire
Janos Farkas	Arthur H. Light	Walter Struppler
Yukihiro Fujimoto	William Lumpkins	Michael Swearingen
David Gregson	Michael Lynch	Patricia Thaler
Randall Groves	Elvis Maculuba	Mark-Rene Uchida
Stephen Haddock	Arthur Marris	Lorenzo Vangelista
Marek Hajduczenia	Jonathon McLendon	Dmitri Varsanofiev
Jerome Henry	Richard Mellitz	George Vlantis
Marco Hernandez	Charles Moorwood	Khurram Waheed
Guido Hiertz	Michael Newman	Stephen Webb
Werner Hoelzl	Nick S.A. Nikjoo	Karl Weber
C. Huntley	Satoshi Obara	Hung-Yu Wei
Noriyuki Ikeuchi	Alon Regev	Natalie Wienckowski
Atsushi Ito	Robert Robinson	Oren Yuen
Tony Jeffree	Benjamin Rolfe	Zhen Zhou

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

When the IEEE-SA Standards Board approved this standard on 30 June 2016, it had the following membership:

Jean-Philippe Faure, *Chair*
Ted Burse, *Vice-Chair*
John D. Kulick, *Past Chair*
Konstantinos Karachalios, *Secretary*

Chuck Adams
Masayuki Ariyoshi
Stephen Dukes
Jianbin Fan
J. Travis Griffith
Gary Hoffman

Ronald W. Hotchkiss
Michael Janezic
Joseph L. Koepfinger*
Hung Ling
Kevin Lu
Annette D. Reilly
Gary Robinson

Mehmet Ulema
Yingli Wen
Howard Wolfman
Don Wright
Yu Yuan
Daidi Zhong

*Member Emeritus

Introduction

This introduction is not part of IEEE Std 802.1Qbu-2016, IEEE Standard for Local and metropolitan area networks—Media Access Control (MAC) Bridges and Virtual Bridged Local Area Networks—Amendment 26: Frame Preemption.

This amendment to IEEE Std 802.1Q-2014 provides enhancements to the forwarding process that support frame preemption.

This standard contains state-of-the-art material. The area covered by this standard is undergoing evolution. Revisions are anticipated within the next few years to clarify existing material, to correct possible errors, and to incorporate new related material. Information on the current revision state of this and other IEEE 802 standards may be obtained from

Secretary, IEEE-SA Standards Board
445 Hoes Lane
Piscataway, NJ 08854
USA

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

Contents

2. Normative references	13
3. Definitions	14
4. Abbreviations	15
5. Conformance	16
5.4 VLAN Bridge component requirements	16
5.13 MAC Bridge component requirements	16
5.26 End station requirements—enhancements for frame preemption	16
6. Support of the MAC Service	17
6.7 Support of the Internal Sublayer Service by specific MAC procedures	17
8. Principles of bridge operation	18
8.6 The Forwarding Process	18
12. Bridge management	20
12.30 Managed objects for frame preemption	20
17. Management Information Base (MIB)	22
17.2 Structure of the MIB	22
17.3 Relationship to other MIBs	22
17.4 Security considerations	23
17.7 MIB modules	23
Annex A (normative) PICS proforma—Bridge implementations	43
A.5 Major capabilities	43
A.14 Bridge management	43
A.24 Management Information Base (MIB)	43
A.44 Frame preemption	44
Annex B (normative) PICS proforma—End station implementations	45
B.5 Major capabilities	45
B.15 Scheduled traffic	45
Annex Q (informative) Preemption and IEEE Std 802.1AE MAC Security	46
Annex R (informative) Preemption and scheduled traffic	48
R.1 Scheduling used in isolation	48
R.2 Preemption used in isolation	48
R.3 Scheduling and preemption used in combination, no HOLD/RELEASE	49
R.4 Scheduling and preemption used in combination, with HOLD/RELEASE	49
R.5 Bandwidth allocation and express traffic	50
Annex S (informative) Bibliography	51

Tables

Table 8-6	Gate operations	19
Table 12-29	Frame Preemption Parameter Ttable	20
Table 17-29	IEEE8021-Preemption-MIB Structure and relationship to this standard	22

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC/IEEE 8802-1Q:2016/Amd 4:2017

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

IEEE Standard for
Local and metropolitan area networks—

Bridges and Bridged Networks— Amendment 26: Frame Preemption

(This amendment is based on IEEE Std 802.1Q™-2014 as amended by IEEE Std 802.1Qbv-2015.)

NOTE—The editing instructions contained in this amendment define how to merge the material contained here into the base document and its other amendments to form the new comprehensive standard.

Editing instructions are shown in ***bold italic***. Four editing instructions are used: change, delete, insert, and replace. ***Change*** is used to make corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed either by using ~~strike through~~ (to remove old material) and underscore (to add new material). ***Delete*** removes existing material. ***Insert*** adds new material without disturbing the existing material. Insertions may require renumbering. If so, renumbering instructions are given in the editing instruction. ***Replace*** is used to make changes in figures or equations by removing the existing figure or equation and replacing it with a new one. Editing instructions, change markings, and this NOTE will not be carried over into future editions because the changes will be incorporated into the base standard.¹

IMPORTANT NOTICE: IEEE Standards documents are not intended to ensure safety, health, or environmental protection, or ensure against interference with or from other devices or networks. Implementers of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

This IEEE document is made available for use subject to important notices and legal disclaimers. These notices and disclaimers appear in all publications containing this document and may be found under the heading “Important Notice” or “Important Notices and Disclaimers Concerning IEEE Documents.” They can also be obtained on request from IEEE or viewed at <http://standards.ieee.org/IPR/disclaimers.html>.

¹Notes in text, tables, and figures are given for information only, and do not contain requirements needed to implement the standard.

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

2. Normative references

Insert the following reference in the appropriate collating sequence:

IEEE Std 802.3br™, IEEE Approved Draft Standard for Ethernet—Amendment 5: Specification and Management Parameters for Interspersing Express Traffic.

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC/IEEE 8802-1Q:2016/Amd 4:2017

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

3. Definitions

Insert the following definition in the appropriate collating sequence and renumber appropriately:

3.x preemption: The suspension of the transmission of a preemptable frame to allow one or more express frames to be transmitted before transmission of the preemptable frame is resumed.

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC/IEEE 8802-1Q:2016/Amd 4:2017

4. Abbreviations

Insert the following definitions in the appropriate collating sequence and renumber appropriately:

eMAC	express Media Access Control
pMAC	preemptable Media Access Control

5. Conformance

5.4 VLAN Bridge component requirements

5.4.1 VLAN Bridge component options

Insert the following list item at the end of the list, relettering as necessary:

- ae) Support frame preemption as specified in 6.7.1, 6.7.2, and 8.6.8.

5.13 MAC Bridge component requirements

5.13.1 MAC Bridge component options

Insert the following list item at the end of the list, relettering as necessary:

- n) Support frame preemption as specified in 6.7.1, 6.7.2, and 8.6.8.

Insert the following new subclause at the end of Clause 5, renumbering as necessary:

5.26 End station requirements—enhancements for frame preemption

An end station implementation that conforms to the provisions of this standard for frame preemption shall

- a) Support the provisions of 6.7.1, 6.7.2, and 8.6.8.

6. Support of the MAC Service

6.7 Support of the Internal Sublayer Service by specific MAC procedures

6.7.1 Support of the Internal Sublayer Service by IEEE Std 802.3 (Ethernet)

Change the first paragraph of 6.7.1 as follows:

In addition to the provisions of 12.1.1 of IEEE Std 802.1AC-2012, an M_CONTROL.request primitive is mapped to an IEEE 802.3 MA_CONTROL.request primitive having the same parameters. If the MAC supports IEEE 802.3br Interspersing Express Traffic, then PFC M_CONTROL.requests are mapped onto the MAC control interface associated with the express MAC (eMAC). An IEEE 802.3 MA_CONTROL.indication primitive is mapped to an M_CONTROL.indication primitive having the same parameters.

Insert new text at the end of 6.7.1 as follows:

If frame preemption (6.7.2) is supported on a Port, then the IEEE 802.3 MAC provides the following two MAC service interfaces (99.4 of IEEE Std 802.3br):

- a) A preemptable MAC (pMAC) service interface, and
- b) An express MAC (eMAC) service interface.

For priority values that are identified in the frame preemption status table (6.7.2) as *preemptable*, frames that are selected for transmission shall be transmitted using the pMAC service instance, and for priority values that are identified in the frame preemption status table as *express*, frames that are selected for transmission shall be transmitted using the eMAC service instance.

In all other respects, the Port behaves as if it is supported by a single MAC service interface. In particular, all frames received by the Port are treated as if they were received on a single MAC service interface regardless of whether they were received on the eMAC service interface or the pMAC service interface, except with respect to frame preemption.

If the value of the holdRequest managed object (12.30.1.5) transitions from FALSE to TRUE, a MM_CTL.request(hold_req) primitive is issued to the underlying IEEE 802.3 MAC, with a hold_req parameter value of HOLD, as described in Clause 99 of IEEE Std 802.3br. If the value of the holdRequest managed object (12.30.1.5) transitions from TRUE to FALSE, a MM_CTL.request(hold_req) primitive is issued to the underlying IEEE 802.3 MAC, with a hold_req parameter value of RELEASE.

NOTE—This additional material will be moved to IEEE Std 802.1AC in a future revision.

Insert new subclause 6.7.2 as follows:

6.7.2 Frame preemption

If the Port supports frame preemption, then a value of frame preemption status is assigned to each value of priority via a *frame preemption status table*. The possible values of frame preemption status are *express* or *preemptable*.

The frame preemption status table can be changed by management as described in 12.30.1.1. The default value of frame preemption status is *express* for all priority values.

8. Principles of bridge operation

8.6 The Forwarding Process

8.6.8 Transmission selection

Insert the following immediately after NOTE 2:

In a port of a Bridge or station that supports frame preemption, a frame of priority n is not available for transmission if that priority is identified in the frame preemption status table (6.7.2) as preemptable and either the holdRequest object (12.30.1.5) is set to the value *hold*, or the transmission of a prior preemptable frame has yet to complete because it has been interrupted to allow the transmission of an express frame.

8.6.8.2 Credit-based shaper algorithm

Change the text of list items e) and f), and insert new NOTES, renumbering subsequent NOTES, as follows:

- e) **transmit.** Takes the value TRUE for the duration of a frame transmission from the queue; FALSE when any frame transmission from the queue has completed. If the credit-based shaper algorithm is used in combination with frame preemption (6.7.2), transmit only takes the value TRUE while the frame is actually being transmitted by the MAC. If the frame transmission is delayed or interrupted (e.g., the frame is a preemptable frame and its transmission is interrupted to allow the transmission of an express frame from a different queue, or the frame is an express frame and there is a delay before transmission can start because a preemptable frame was being transmitted) transmit takes the value FALSE until transmission of the frame commences or is resumed. Transmit also takes the value FALSE during the transmission of any overhead that is a consequence of frame preemption; i.e., any additional frame overhead that is added to the preemptable frame when preemption occurs.

NOTE 1—The consequence of this is that any overhead associated with preemption does not come out of the reserved bandwidth for the credit-based shaper.

- f) **credit.** The transmission credit, in bits, that is currently available to the queue. If, at any time, there are no frames in the queue, and the *transmit* parameter is FALSE, and the transmission gate for the queue is open (8.6.8.4), and *credit* is positive, and there is no preemptable frame from this queue for which transmission is in progress but has been interrupted, then *credit* is set to zero.

NOTE 2—The condition that the *transmit* parameter is FALSE and a preemptable frame or part-frame is waiting in the MAC for transmission can only occur if the credit-based shaper algorithm is used in combination with Preemption.

8.6.8.4 Enhancements for scheduled traffic

Change the second paragraph of 8.6.8.4 as follows:²

A gate control list associated with each Port contains an ordered list of gate operations. Each gate operation changes the transmission gate state for the gate associated with each of the Port's traffic class queues and allows associated control operations to be scheduled. In an implementation that does not support enhancements for scheduled traffic, all gates are assumed to be permanently in the *open* state. Table 8-6 identifies the gate operation types, their parameters, and the actions that result from their execution. The state machines that control the execution of the gate control list, along with their variables and procedures, are specified in 8.6.9.

²The base text of 8.6.8.4 is to be found in IEEE Std 802.1Qbv-2016.

Insert two new rows at the end of Table 8-6 as follows:

Table 8-6—Gate operations

Operation name	Parameter(s)	Action
Set-And-Hold-MAC	GateState, TimeInterval	Performs all of the actions defined for the SetGateStates operation; ¹ in addition, the start of this operation marks the point in the sequence of gate operations at which the MAC associated with the port is to have stopped transmitting preemptable frames. This is achieved by setting the holdRequest managed object to the value <i>hold</i> (1), at holdAdvance (Table 12-29) nanoseconds in advance of this point for the hold to have taken effect at this point. If frame preemption is not supported or not enabled (preemptionActive is FALSE), this operation behaves the same as SetGateStates.
Set-And-Release-MAC	GateState, TimeInterval	Performs all of the actions defined for the SetGateStates operation; in addition, the start of this operation marks the point in the sequence of gate operations at which the MAC associated with the port is permitted to resume transmitting preemptable frames; if an express frame is currently being transmitted by the MAC, the release takes effect at the end of that transmission. This is achieved by setting the holdRequest managed object to the value <i>release</i> (2), at releaseAdvance (Table 12-29) nanoseconds in advance of this point for the release to have taken effect at this point. ² If frame preemption is not supported or not enabled (preemptionActive is FALSE), this operation behaves the same as SetGateStates.

¹The SetGateStates operation is defined in IEEE Std 802.1Qbv-2016.

²The releaseAdvance parameter allows the timing of when the release command is issued to vary depending upon the constraints of a particular implementation. Its value should be less than the minimum frame size so that release does not occur too early and interfere with transmission of the last express frame.

12. Bridge management

Insert new subclause 12.30 and its subclauses and tables, as follows, renumbering as necessary:

12.30 Managed objects for frame preemption

The Bridge enhancements for support of frame preemption are defined in 8.6.8, 8.6.8.4, and 6.7.2. The objects that comprise this managed resource are as follows:

a) Frame Preemption Parameter Table (12.30.1)

12.30.1 Frame Preemption Parameter table

There is one Frame Preemption Parameter table per Port of a Bridge component or end station. Each table row contains a set of parameters that supports the enhancements for frame preemption (6.7.2), as detailed in Table 12-29. Rows in the table can be created or removed dynamically in implementations that support dynamic configuration of ports and components.

Table 12-29—Frame Preemption Parameter table

Name	Data type	Operations supported ^a	Conformance ^b	References
framePreemptionStatusTable	sequence of framePreemptionAdminStatus values	RW	BE	6.7.2, 12.30.1.1, 12.30.1.1.1.
holdAdvance	Integer, nanoseconds	R	BE	Table 8-6, 12.30.1.2
releaseAdvance	Integer, nanoseconds	R	BE	Table 8-6, 12.30.1.3
preemptionActive	Boolean	R	BE	12.30.1.4
holdRequest	Integer {hold (1), release (2)}	R	BE	Table 8-6, 12.30.1.5

^aR = Read only access; RW = Read/Write access

^bB = Required for Bridge or Bridge component support of enhancements for frame preemption.

E = Required for end station support of enhancements for frame preemption.

12.30.1.1 framePreemptionStatusTable structure and data types

The framePreemptionStatusTable (6.7.2) consists of 8 framePreemptionAdminStatus values (12.30.1.1.1), one per priority.

12.30.1.1.1 framePreemptionAdminStatus

This parameter is the administrative value of the preemption status for the priority. It takes value *express* if frames queued for the priority are to be transmitted using the express service for the Port, or *preemptable* if frames queued for the priority are to be transmitted using the preemptable service for the Port and preemption is enabled for the Port.

Priorities that all map to the same traffic class should be constrained to use the same value of preemption status.

12.30.1.2 holdAdvance object

The holdAdvance object contains an integer value representing the maximum number of nanoseconds that can elapse between issuing a HOLD (12.30.1.5) to the MAC and the MAC ceasing to transmit any preemptable frame that is in the process of transmission or any preemptable frames that are queued for transmission, including any MAC-specific delay before transmission of an express frame could start once preemptable frame transmission has ceased. This object exists per Port, and is a characteristic of the underlying MAC.

12.30.1.3 releaseAdvance object

The releaseAdvance object contains an integer value representing the maximum number of nanoseconds that can elapse between issuing a RELEASE (12.30.1.5) to the MAC and the MAC being ready to resume transmission of preemptable frames, in the absence of there being any express frames available for transmission. This object exists per Port, and is a characteristic of the underlying MAC.

12.30.1.4 preemptionActive object

TRUE if preemption is both supported by the MAC and currently active.

12.30.1.5 holdRequest object

The holdRequest object contains an enumerated integer value, with *hold* (1) indicating that a Set-And-Hold-MAC gate operation (8.6.8.4, Table 8-6) has been executed, and *release* (2) indicating that a Set-And-Release-MAC gate operation has been executed. This object exists per Port.

NOTE—In order to determine support of frame preemption by the Bridge, a network management application could attempt to read the preemptionActive object. If the read operation returns an error, frame preemption is not supported. Determining whether the MAC supports preemption could similarly be achieved by examining the objects in the MAC MIB.

17. Management Information Base (MIB)

17.2 Structure of the MIB

Insert the following new subclause 17.2.23 and Table 17-29 at the end of 17.2, renumbering as necessary:

17.2.23 Structure of the IEEE8021-Preemption-MIB

The IEEE8021-Preemption-MIB provides for configuration of frame preemption (6.7.2, 8.6.8) on ports. Table 17-29 indicates the relationship between the SMIV2 objects defined in the MIB module (17.7.23) and managed objects defined in 12.30.

Table 17-29—IEEE8021-Preemption-MIB Structure and relationship to this standard

MIB table	MIB object	Reference
<i>ieee8021PreemptionParameterTable subtree</i>		
ieee8021PreemptionParameterTable		Frame Preemption parameter table, 6.7.2, 12.30.1
	ieee8021PreemptionPriority	Priority (Table index)
	ieee8021FramePreemptionAdminStatus	framePreemptionAdminStatus, 6.7.2, 12.30.1
ieee8021PreemptionConfigTable		Frame Preemption configuration table, 6.7.2, 12.30.1
	ieee8021FramePreemptionHoldAdvance	framePreemptionHoldAdvance, 6.7.2, 12.30.1, 12.30.1.2
	ieee8021FramePreemptionReleaseAdvance	framePreemptionReleaseAdvance, 6.7.2, 12.30.1, 12.30.1.3
	ieee8021FramePreemptionActive	framePreemptionActive, 6.7.2, 12.30.1, 12.30.1.4
	ieee8021FramePreemptionHoldRequest	framePreemptionHoldRequest, 6.7.2, 12.30.1, 12.30.1.5

17.3 Relationship to other MIBs

Insert the following new subclause 17.3.23 at the end of 17.3, renumbering as necessary:

17.3.23 Relationship of the IEEE8021-Preemption-MIB to other MIBs

The IEEE8021-Preemption-MIB provides objects that extend the core management functionality of a Bridge, as defined by the IEEE8021-BRIDGE-MIB (17.7.2), in order to support the additional management functionality needed when the frame preemption extensions are supported by the Bridge. As support of the objects defined in the IEEE8021-Preemption-MIB also requires support of the IEEE8021-BRIDGE-MIB, the provisions of 17.3.2 apply to implementations claiming support of the IEEE8021-Preemption-MIB.

17.4 Security considerations

Insert the following new subclause 17.4.23 at the end of 17.4, renumbering as necessary:

17.4.23 Security considerations of the IEEE8021-ST-MIB

There is one management object defined in the IEEE8021-Preemption-MIB module that has a MAX-ACCESS clause of read-write. Such objects may be considered sensitive or vulnerable in some network environments. The support for SET operations in a nonsecure environment without proper protection can have a negative effect on network operations.

Some of the readable objects in this MIB module (i.e., objects with a MAX-ACCESS other than not-accessible) may be considered sensitive or vulnerable in some network environments. It is thus important to control all types of access (including GET and/or NOTIFY) to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP.

The following tables and objects in the IEEE8021-Preemption-MIB can be manipulated to interfere with the operation of the forwarding and queuing mechanisms in a manner that would be detrimental to the transmission of frames:

ieee8021FramePreemptionAdminStatus

- a) Misconfiguration of the ieee8021FramePreemptionAdminStatus object can lead to the degradation of the quality of service for the application on the port at the respective traffic class that is wrongly preempted, or to the saturation of the priority queues on the port because of preemptable traffic classes receiving express processing.

17.7 MIB modules

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

Replace subclause 17.7.22 with the following:

17.7.22 Definitions for the IEEE8021-ST-MIB module

IEEE8021-ST-MIB DEFINITIONS ::= BEGIN

```
-- =====
-- MIB for support of the Scheduled Traffic Enhancements
-- for IEEE 802.1Q Bridges.
-- =====
```

IMPORTS

```
MODULE-IDENTITY,
OBJECT-TYPE,
Unsigned32,
Counter64
    FROM SNMPv2-SMI
TEXTUAL-CONVENTION,
TruthValue
    FROM SNMPv2-TC
MODULE-COMPLIANCE,
OBJECT-GROUP
    FROM SNMPv2-CONF
ieee802dot1mibs
    FROM IEEE8021-TC-MIB
ieee8021BridgeBaseComponentId,
ieee8021BridgeBasePort
    FROM IEEE8021-BRIDGE-MIB
;
```

ieee8021STMib MODULE-IDENTITY

```
LAST-UPDATED "201608150000Z" -- August 15, 2016
ORGANIZATION "IEEE 802.1 Working Group"
CONTACT-INFO
    " WG-URL: www.ieee802.org/1
      WG-E-Mail: STDS-802-1-L@listserv.ieee.org
```

```
    Contact: IEEE 802.1 Working Group Chair
    Postal: C/O IEEE 802.1 Working Group
            IEEE Standards Association
            445 Hoes Lane
            Piscataway
            NJ 08854
            USA
```

```
    E-mail: STDS-802-1-L@listserv.ieee.org"
```

DESCRIPTION

```
"The Bridge MIB module for managing devices that support
the Scheduled Traffic Enhancements
for 802.1Q Bridges.
```

```
Unless otherwise indicated, the references in this MIB
module are to IEEE Std 802.1Q-2014.
```

```
Copyright (C) IEEE (2014).
```

```
This version of this MIB module is part of IEEE802.1Q;
see the draft itself for full legal notices."
```

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

REVISION "201608150000Z" -- August 15, 2016

DESCRIPTION

"Revised to include Set-And-Hold-MAC and
Set-And-Release-MAC in the description of
ieee8021STAdminControlList and
ieee8021STOperControlList.
Published as part of IEEE Std 802.1Qbu."

REVISION "201509250000Z" -- September 25, 2015

DESCRIPTION

"Initial version published as part of IEEE Std 802.1Qbv."

::= { ieee802dot1mibs 30 }

-- =====
-- Textual Conventions
-- =====

IEEE8021STTrafficClassValue ::= TEXTUAL-CONVENTION

DISPLAY-HINT "d"

STATUS current

DESCRIPTION

"A traffic class value.
This is the numerical value associated with a traffic
class in a Bridge. Larger values are associated with
higher priority traffic classes."

REFERENCE "12.29.1"

SYNTAX Unsigned32 (0..7)

IEEE8021STPTptimeValue ::= TEXTUAL-CONVENTION

STATUS current

DESCRIPTION

"A PTptime value, represented as a 48-bit unsigned integer
number of seconds and a 32-bit unsigned integer number of
nanoseconds.
The first 6 octets represent the number of seconds: the
first octet is the most significant
octet of the 48-bit seconds value and the sixth octet
is the least significant octet of the seconds value.
The remaining octets, 7 through 10, represent the
number of nanoseconds: the seventh octet
is the most significant octet of the 32-bit nanoseconds
value and the tenth octet is the
least significant octet of the nanoseconds value."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

SYNTAX OCTET STRING (SIZE(10))

-- =====
-- subtrees in the ST MIB
-- =====

ieee8021STNotifications

OBJECT IDENTIFIER ::= { ieee8021STMib 0 }

ieee8021STObjects

OBJECT IDENTIFIER ::= { ieee8021STMib 1 }

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

```

ieee8021STConformance
    OBJECT IDENTIFIER ::= { ieee8021STMib 2 }

ieee8021STMaxSDUSubtree
    OBJECT IDENTIFIER ::= { ieee8021STObjects 1 }

ieee8021STParameters
    OBJECT IDENTIFIER ::= { ieee8021STObjects 2 }

-- =====
-- The ieee8021STMaxSDUSubtree subtree
-- This subtree defines the objects necessary for the management
-- of the max SDU size parameters for each traffic class on a Port.
-- =====

-- =====
-- the ieee8021STMaxSDUTable
-- =====

ieee8021STMaxSDUTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF Ieee8021STMaxSDUEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A table containing a set of max SDU
        parameters, one for each traffic class.
        All writeable objects in this table must be
        persistent over power up restart/reboot."
    REFERENCE   "8.6.8.4, 8.6.9.4, 12.29.1"
    ::= { ieee8021STMaxSDUSubtree 1 }

ieee8021STMaxSDUEntry OBJECT-TYPE
    SYNTAX      Ieee8021STMaxSDUEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A list of objects containing Max SDU size
        for each traffic class supported by the Port."
    INDEX { ieee8021BridgeBaseComponentId,
            ieee8021BridgeBasePort,
            ieee8021STTrafficClass }
    ::= { ieee8021STMaxSDUTable 1 }

Ieee8021STMaxSDUEntry ::=
    SEQUENCE {
        ieee8021STTrafficClass
            IEEE8021STTrafficClassValue,
        ieee8021STMaxSDU
            Unsigned32,
        ieee8021TransmissionOverrun
            Counter64
    }

ieee8021STTrafficClass OBJECT-TYPE
    SYNTAX      IEEE8021STTrafficClassValue
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "The traffic class number associated with the row of

```

the table.

A row in this table is created for each traffic class that is supported by the Port"

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STMaxSDUEntry 1 }

ieee8021STMaxSDU OBJECT-TYPE

SYNTAX Unsigned32

UNITS "octets"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The value of the MaxSDU parameter for the traffic class. This value is represented as an unsigned integer. A value of 0 is interpreted as the max SDU size supported by the underlying MAC.

The default value of the MaxSDU parameter is 0.

The value of this object MUST be retained across reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

DEFVAL { 0 }

::= { ieee8021STMaxSDUEntry 2 }

ieee8021TransmissionOverrun OBJECT-TYPE

SYNTAX Counter64

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A counter of transmission overrun events, where a PDU is still being transmitted by a MAC at the time when the transmission gate for the queue closed."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1, 12.29.1.1.2"

DEFVAL { 0 }

::= { ieee8021STMaxSDUEntry 2 }

```
-- =====
-- The ieee8021STParameters subtree
-- This subtree defines the objects necessary for the management
-- of the traffic scheduling mechanism for IEEE Std 802.1Q.
-- =====
--
-- =====
-- the ieee8021STParametersTable
-- =====
```

ieee8021STParametersTable OBJECT-TYPE

SYNTAX SEQUENCE OF Ieee8021STParametersEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A table that contains the per-port manageable parameters for traffic scheduling.

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

For a given Port, a row in the table exists.

All writable objects in this table must be persistent over power up restart/reboot."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParameters 1 }

ieee8021STParametersEntry OBJECT-TYPE

SYNTAX Ieee8021STParametersEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of objects that contains the manageable parameters for traffic scheduling for a port."

INDEX { ieee8021BridgeBaseComponentId,
ieee8021BridgeBasePort
}

::= { ieee8021STParametersTable 1 }

Ieee8021STParametersEntry ::=

SEQUENCE {

ieee8021STGateEnabled

TruthValue,

ieee8021STAdminGateStates

OCTET STRING,

ieee8021STOperGateStates

OCTET STRING,

ieee8021STAdminControllListLength

Unsigned32,

ieee8021STOperControllListLength

Unsigned32,

ieee8021STAdminControllList

OCTET STRING,

ieee8021STOperControllList

OCTET STRING,

ieee8021STAdminCycleTimeNumerator

Unsigned32,

ieee8021STAdminCycleTimeDenominator

Unsigned32,

ieee8021STOperCycleTimeNumerator

Unsigned32,

ieee8021STOperCycleTimeDenominator

Unsigned32,

ieee8021STAdminCycleTimeExtension

Unsigned32,

ieee8021STOperCycleTimeExtension

Unsigned32,

ieee8021STAdminBaseTime

IEEE8021STPTPtimeValue,

ieee8021STOperBaseTime

IEEE8021STPTPtimeValue,

ieee8021STConfigChange

TruthValue,

ieee8021STConfigChangeTime

IEEE8021STPTPtimeValue,

ieee8021STTickGranularity

Unsigned32,

ieee8021STCurrentTime

IEEE8021STPTPtimeValue,

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

```
ieee8021STConfigPending
    TruthValue,
ieee8021STConfigChangeError
    Counter64,
ieee8021STSupportedListMax
    Unsigned32
}
```

ieee8021STGateEnabled OBJECT-TYPE

```
SYNTAX      TruthValue
MAX-ACCESS  read-write
STATUS      current
```

DESCRIPTION

"The GateEnabled parameter determines whether traffic scheduling is active (true) or inactive (false).

The value of this object MUST be retained across reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

DEFVAL { false }

::= { ieee8021STParametersEntry 1 }

ieee8021STAdminGateStates OBJECT-TYPE

```
SYNTAX      OCTET STRING (SIZE(1))
MAX-ACCESS  read-write
STATUS      current
```

DESCRIPTION

"The administrative value of the GateStates parameter for the Port. The bits of the octet represent the gate states for the corresponding traffic classes; the MS bit corresponds to traffic class 7, the LS bit to traffic class 0. A bit value of 0 indicates closed; a bit value of 1 indicates open.

The value of this object MUST be retained across reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 2 }

ieee8021STOperGateStates OBJECT-TYPE

```
SYNTAX      OCTET STRING (SIZE(1))
MAX-ACCESS  read-only
STATUS      current
```

DESCRIPTION

"The operational value of the GateStates parameter for the Port. The bits of the octet represent the gate states for the corresponding traffic classes; the MS bit corresponds to traffic class 7, the LS bit to traffic class 0. A bit value of 0 indicates closed; a bit value of 1 indicates open."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 3 }

ieee8021STAdminControlListLength OBJECT-TYPE

```
SYNTAX      Unsigned32
MAX-ACCESS  read-write
STATUS      current
```

DESCRIPTION

"The administrative value of the ListMax parameter for the Port. The integer value indicates the number of entries (TLVs) in the AdminControlList.

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

The value of this object MUST be retained across reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"
::= { ieee8021STParametersEntry 4 }

ieee8021STOperControlListLength OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The operational value of the ListMax parameter for the Port.

The integer value indicates the number of entries (TLVs) in the OperControlList."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"
::= { ieee8021STParametersEntry 5 }

ieee8021STAdminControlList OBJECT-TYPE

SYNTAX OCTET STRING

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The administrative value of the ControlList parameter for the Port.

The octet string value represents the contents of the control list as an ordered list of entries, each encoded as a TLV, as follows.

The first octet of each TLV is interpreted as an unsigned integer representing a gate operation name:

- 0: SetGateStates
- 1: Set-And-Hold-MAC
- 2: Set-And-Release-MAC
- 3-255: Reserved for future gate operations

The second octet of the TLV is the length field, interpreted as an unsigned integer, indicating the number of octets of the value that follows the length. A length of zero indicates that there is no value (i.e., the gate operation has no parameters).

The third through (3 + length -1)th octets encode the parameters of the gate operation, in the order that they appear in the definition of the operation in Table 8-6. Two parameter types are currently defined:

- GateState:

A GateState parameter is encoded in a single octet. The bits of the octet represent the gate states for the corresponding traffic classes; the MS bit corresponds to traffic class 7, the LS bit to traffic class 0. A bit value of 0 indicates closed; a bit value of 1 indicates open.

- TimeInterval:

A TimeInterval is encoded in 4 octets as a 32-bit unsigned integer, representing a number of nanoseconds. The first octet encodes the most significant 8 bits of the integer, and the fourth octet encodes the least significant 8 bits.

The value of this object MUST be retained across

reinitializations of the management system."
REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"
::= { ieee8021STParametersEntry 6 }

ieee8021STOperControlList OBJECT-TYPE

SYNTAX OCTET STRING
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"The operational value of the ListMax parameter for the Port.
The octet string value represents the contents of the control list as
an ordered list of TLVs, as follows.
The first octet of each TLV is interpreted as a gate operation name.
0: SetGateStates
1: Set-And-Hold-MAC
2: Set-And-Release-MAC
3-255: Reserved for future gate operations

The second octet of the TLV is the length field,
interpreted as an unsigned integer,
indicating the number of octets of the value that follows
the length. A length of zero indicates that there is no value
(i.e., the gate operation has no parameters).

The third through (3 + length -1)th octets encode the
parameters of the gate operation, in the order that they
appear in the definition of the operation
in Table 8-6. Two parameter types are currently defined:

- GateState:
A GateState parameter is encoded in a single octet.
The bits of the octet represent the gate states for the
corresponding traffic classes; the MS bit corresponds to
traffic class 7, the LS bit to traffic class 0.
A bit value of 0 indicates closed; a
bit value of 1 indicates open.
- TimeInterval:
A TimeInterval is encoded in 4 octets as a 32-bit
unsigned integer, representing
a number of nanoseconds. The first octet encodes the
most significant 8 bits of the integer, and the fourth
octet encodes the least significant 8 bits."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"
::= { ieee8021STParametersEntry 7 }

ieee8021STAdminCycleTimeNumerator OBJECT-TYPE

SYNTAX Unsigned32
MAX-ACCESS read-write
STATUS current

DESCRIPTION

"The administrative value of the numerator of the CycleTime
parameter for the Port.
The numerator and denominator together represent the cycle time as
a rational number of seconds.

The value of this object MUST be retained across
reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

::= { ieee8021STParametersEntry 8 }

ieee8021STAdminCycleTimeDenominator OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The administrative value of the denominator of the
CycleTime parameter for the Port.

The numerator and denominator together represent the cycle time as
a rational number of seconds.

The value of this object MUST be retained across
reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 9 }

ieee8021STOperCycleTimeNumerator OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The operational value of the numerator of the
CycleTime parameter for the Port.

The numerator and denominator together represent the cycle
time as a rational number of seconds."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 10 }

ieee8021STOperCycleTimeDenominator OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The operational value of the denominator of the
CycleTime parameter for the Port.

The numerator and denominator together represent the
cycle time as a rational number of seconds."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 11 }

ieee8021STAdminCycleTimeExtension OBJECT-TYPE

SYNTAX Unsigned32

UNITS "nanoseconds"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The administrative value of the CycleTimeExtension
parameter for the Port.

The value is an unsigned integer number of nanoseconds.

The value of this object MUST be retained across
reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 12 }

ieee8021STOperCycleTimeExtension OBJECT-TYPE

SYNTAX Unsigned32

UNITS "nanoseconds"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The operational value of the CycleTimeExtension parameter for the Port.

The value is an unsigned integer number of nanoseconds."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 13 }

ieee8021STAdminBaseTime OBJECT-TYPE

SYNTAX IEEE8021STPTtimeValue

UNITS "PTP time"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The administrative value of the BaseTime parameter for the Port.

The value is a representation of a PTtime value,
consisting of a 48-bit integer
number of seconds and a 32-bit integer number of nanoseconds.

The value of this object MUST be retained across
reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 14 }

ieee8021STOperBaseTime OBJECT-TYPE

SYNTAX IEEE8021STPTtimeValue

UNITS "PTP time"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The operationsl value of the BaseTime parameter for the Port.

The value is a representation of a PTtime value,
consisting of a 48-bit integer
number of seconds and a 32-bit integer number of nanoseconds."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 15 }

ieee8021STConfigChange OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The ConfigChange parameter signals the start of a
configuration change

when it is set to TRUE. This should only be done
when the various administrative parameters
are all set to appropriate values."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 16 }

ieee8021STConfigChangeTime OBJECT-TYPE

SYNTAX IEEE8021STPTtimeValue

UNITS "PTP time"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The PTtime at which the next config change is scheduled to occur.

The value is a representation of a PTtime value,
consisting of a 48-bit integer

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

number of seconds and a 32-bit integer number of nanoseconds.

The value of this object MUST be retained across reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 17 }

ieee8021STTickGranularity OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The granularity of the cycle time clock, represented as an unsigned number of tenths of nanoseconds.

The value of this object MUST be retained across reinitializations of the management system."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 18 }

ieee8021STCurrentTime OBJECT-TYPE

SYNTAX IEEE8021STPTptimeValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The current time, in PTptime, as maintained by the local system.

The value is a representation of a PTptime value,

consisting of a 48-bit integer

number of seconds and a 32-bit integer number of nanoseconds."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 19 }

ieee8021STConfigPending OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The value of the ConfigPending state machine variable.

The value is TRUE if a configuration change is in progress but has not yet completed."

REFERENCE "8.6.8.4, 8.6.9.4, 12.29.1"

::= { ieee8021STParametersEntry 20 }

ieee8021STConfigChangeError OBJECT-TYPE

SYNTAX Counter64

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A counter of the number of times that a re-configuration of the traffic schedule has been requested with the old schedule still running and the requested base time was in the past."

REFERENCE "8.6.8.4, 8.6.9.3, 8.6.9.1.1, 12.29.1"

::= { ieee8021STParametersEntry 21 }

ieee8021STSupportedListMax OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The maximum value supported by this Port of the AdminControlListLength and OperControlListLength parameters."

REFERENCE "12.29.1.5"

::= { ieee8021STParametersEntry 22 }

```
-- =====
-- IEEE8021 FQTSS MIB - Conformance Information
-- =====

ieee8021STCompliances
  OBJECT IDENTIFIER ::= { ieee8021STConformance 1 }
ieee8021STGroups
  OBJECT IDENTIFIER ::= { ieee8021STConformance 2 }

-- =====
-- units of conformance
-- =====

-- =====
-- the ieee8021STObjectsGroup group
-- =====

ieee8021STObjectsGroup OBJECT-GROUP
  OBJECTS {
    ieee8021STMaxSDU,
    ieee8021STTransmissionOverrun,
    ieee8021STGateEnabled,
    ieee8021STAdminGateStates,
    ieee8021STOperGateStates,
    ieee8021STAdminControlListLength,
    ieee8021STOperControlListLength,
    ieee8021STAdminControlList,
    ieee8021STOperControlList,
    ieee8021STAdminCycleTimeNumerator,
    ieee8021STAdminCycleTimeDenominator,
    ieee8021STOperCycleTimeNumerator,
    ieee8021STOperCycleTimeDenominator,
    ieee8021STAdminCycleTimeExtension,
    ieee8021STOperCycleTimeExtension,
    ieee8021STAdminBaseTime,
    ieee8021STOperBaseTime,
    ieee8021STConfigChange,
    ieee8021STConfigChangeTime,
    ieee8021STTickGranularity,
    ieee8021STCurrentTime,
    ieee8021STConfigPending,
    ieee8021STConfigChangeError,
    ieee8021STSupportedListMax
  }
  STATUS      current
  DESCRIPTION
    "Objects that allow management of scheduled traffic."
    ::= { ieee8021STGroups 1 }

-- =====
```

IEEE Std 802.1Qbu-2016
 IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
 Amendment 26: Frame Preemption

-- compliance statements

-- =====

ieee8021STCompliance MODULE-COMPLIANCE

STATUS current

DESCRIPTION

"The compliance statement for devices supporting
 scheduled traffic.

Support of the objects defined in this MIB module
 also requires support of the IEEE8021-BRIDGE-MIB; the
 provisions of 17.3.2 apply to implementations claiming
 support of this MIB."

MODULE -- this module

MANDATORY-GROUPS {

ieee8021STObjectsGroup

}

::= { ieee8021STCompliances 1 }

END

Insert the following new subclause 17.7.23 at the end of 17.7, renumbering as necessary:

17.7.23 Definitions for the IEEE8021-Preemption-MIB module

IEEE8021-Preemption-MIB DEFINITIONS ::= BEGIN

```
-- =====
-- MIB for support of the frame preemption enhancements
-- for IEEE 802.1Q Bridges.
-- =====
```

IMPORTS

```
MODULE-IDENTITY,
OBJECT-TYPE,
Unsigned32
    FROM SNMPv2-SMI
MODULE-COMPLIANCE,
OBJECT-GROUP
    FROM SNMPv2-CONF
ieee802dot1mibs,
IEEE8021PriorityValue
    FROM IEEE8021-TC-MIB
ieee8021BridgeBaseComponentId,
ieee8021BridgeBasePort
    FROM IEEE8021-BRIDGE-MIB
;
```

ieee8021PreemptionMib MODULE-IDENTITY

```
LAST-UPDATED "201608150000Z" -- August 15, 2016
ORGANIZATION "IEEE 802.1 Working Group"
CONTACT-INFO
    " WG-URL: www.ieee802.org/1
    WG-Email: STDS-802-1-L@listserv.ieee.org
```

```
    Contact: IEEE 802.1 Working Group Chair
    Postal: C/O IEEE 802.1 Working Group
            IEEE Standards Association
            445 Hoes Lane
            Piscataway
            NJ 08854
            USA
```

```
    E-mail: STDS-802-1-L@listserv.ieee.org"
```

DESCRIPTION

```
"The Bridge MIB module for managing devices that support
the frame preemption enhancements
for 802.1Q Bridges.
```

```
Unless otherwise indicated, the references in this MIB
module are to IEEE Std 802.1Q-2014.
```

```
Copyright (C) IEEE (2014).
```

```
This version of this MIB module is part of IEEE802.1Q;
see the draft itself for full legal notices."
```

REVISION "201608150000Z" -- August 15, 2016

DESCRIPTION

```
"Initial version published as part of IEEE Std 802.1Qbu."
```


IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

```
::= { ieee802dot1mibs 29 }
```

```
-- =====
-- subtrees in the Preemption MIB
-- =====

ieee8021PreemptionNotifications
  OBJECT IDENTIFIER ::= { ieee8021PreemptionMib 0 }

ieee8021PreemptionObjects
  OBJECT IDENTIFIER ::= { ieee8021PreemptionMib 1 }

ieee8021PreemptionConformance
  OBJECT IDENTIFIER ::= { ieee8021PreemptionMib 2 }

ieee8021PreemptionParameters
  OBJECT IDENTIFIER ::= { ieee8021PreemptionObjects 1 }

-- =====
-- The ieee8021PreemptionNotifications subtree
-- This subtree defines any notifications necessary for the management
-- of frame preemption on a Port. This subtree is currently unused,
-- but is retained as a place-holder for future standardisation.
-- =====

-- =====
-- The ieee8021PreemptionParameters subtree
-- This subtree defines the objects necessary for the management
-- of the frame preemption parameters for each priority value
-- on a Port.
-- =====

-- =====
-- the ieee8021PreemptionParameterTable
-- =====

ieee8021PreemptionParameterTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF Ieee8021PreemptionParameterEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A table containing a set of frame preemption
        parameters, one for each priority value.
        All writeable objects in this table must be
        persistent over power up restart/reboot."
    REFERENCE   "6.7.2, 12.30.1"
    ::= { ieee8021PreemptionParameters 1 }

ieee8021PreemptionParameterEntry OBJECT-TYPE
    SYNTAX      Ieee8021PreemptionParameterEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A list of objects containing preemption parameters
        for each priority value."
    INDEX { ieee8021BridgeBaseComponentId,
            ieee8021BridgeBasePort,
```

```

ieee8021PreemptionPriority }
 ::= { ieee8021PreemptionParameterTable 1 }

Ieee8021PreemptionParameterEntry ::=
    SEQUENCE {
        ieee8021PreemptionPriority
        IEEE8021PriorityValue,
        ieee8021FramePreemptionAdminStatus
        INTEGER
    }

ieee8021PreemptionPriority OBJECT-TYPE
    SYNTAX      IEEE8021PriorityValue
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "The priority number associated with the row of
        the table.

        A row in this table is created for each priority value."
    REFERENCE   "6.7.2, 12.30.1"
    ::= { ieee8021PreemptionParameterTable 1 }

ieee8021FramePreemptionAdminStatus OBJECT-TYPE
    SYNTAX      INTEGER {express (1), preemptable (2)}
    MAX-ACCESS  read-write
    STATUS      current
    DESCRIPTION
        "The value of the framePreemptionAdminStatus parameter
        for the traffic class.

        The default value of the framePreemptionAdminStatus parameter
        is express (1).

        The value of this object MUST be retained across
        reinitializations of the management system."
    REFERENCE   "6.7.2, 12.30.1"
    ::= { ieee8021PreemptionParameterTable 2}

-- =====
-- the ieee8021PreemptionConfigTable
-- =====

ieee8021PreemptionConfigTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF Ieee8021PreemptionConfigEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A table containing a set of frame preemption
        parameters, one for each Port.
        All writeable objects in this table must be
        persistent over power up restart/reboot."
    REFERENCE   "6.7.2, 12.30.1"
    ::= { ieee8021PreemptionParameters 2 }

ieee8021PreemptionConfigEntry OBJECT-TYPE
    SYNTAX      Ieee8021PreemptionConfigEntry

```

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

MAX-ACCESS not-accessible
STATUS current
DESCRIPTION
"A list of objects containing preemption parameters
for each Port."
INDEX { ieee8021BridgeBaseComponentId,
ieee8021BridgeBasePort }
::= { ieee8021PreemptionConfigTable 1 }

Ieee8021PreemptionConfigEntry ::=
SEQUENCE {
ieee8021FramePreemptionHoldAdvance
Unsigned32,
ieee8021FramePreemptionReleaseAdvance
Unsigned32,
ieee8021FramePreemptionActive
INTEGER,
ieee8021FramePreemptionHoldRequest
INTEGER
}

ieee8021FramePreemptionHoldAdvance OBJECT-TYPE
SYNTAX Unsigned32
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"The value of the holdAdvance parameter
for the Port in nanoseconds.

There is no default value; the holdAdvance is
a property of the underlying MAC."
REFERENCE "6.7.2, 12.30.1.2"
::= { ieee8021PreemptionConfigEntry 1 }

ieee8021FramePreemptionReleaseAdvance OBJECT-TYPE
SYNTAX Unsigned32
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"The value of the releaseAdvance parameter
for the Port in nanoseconds.

There is no default value; the releaseAdvance is
a property of the underlying MAC."
REFERENCE "6.7.2, 12.30.1.3"
::= { ieee8021PreemptionConfigEntry 2 }

ieee8021FramePreemptionActive OBJECT-TYPE
SYNTAX INTEGER {idle (1), active (2)}
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"The value is active (2) when preemption is operationally
active for the Port, and idle (1) otherwise."
REFERENCE "6.7.2, 12.30.1.4"
::= { ieee8021PreemptionConfigEntry 3 }

ieee8021FramePreemptionHoldRequest OBJECT-TYPE

IEEE Std 802.1Qbu-2016
IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks—
Amendment 26: Frame Preemption

SYNTAX INTEGER {hold (1), release (2)}

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The value is hold (1) when the sequence of gate operations for the Port has executed a Set-And-Hold-MAC operation, and release (2) when the sequence of gate operations has executed a Set-And-Release-MAC operation. The value of this object is release (2) on system initialization."

REFERENCE "6.7.2, Table 8-6, 12.30.1.5"

::= { ieee8021PreemptionConfigEntry 4 }

```
-- =====
-- IEEE8021 Preemption MIB - Conformance Information
-- =====
```

ieee8021PreemptionCompliances

OBJECT IDENTIFIER ::= { ieee8021PreemptionConformance 1 }

ieee8021PreemptionGroups

OBJECT IDENTIFIER ::= { ieee8021PreemptionConformance 2 }

```
-- =====
-- units of conformance
-- =====
```

```
-- =====
-- the ieee8021PreemptionGroup group
-- =====
```

ieee8021PreemptionGroup OBJECT-GROUP

OBJECTS {

ieee8021FramePreemptionAdminStatus,
ieee8021FramePreemptionHoldAdvance,
ieee8021FramePreemptionReleaseAdvance,
ieee8021FramePreemptionActive,
ieee8021FramePreemptionHoldRequest

}

STATUS current

DESCRIPTION

"Objects that allow management of frame preemption."

::= { ieee8021PreemptionGroups 1 }

```
-- =====
-- compliance statements
-- =====
```

ieee8021PreemptionCompliance MODULE-COMPLIANCE

STATUS current

DESCRIPTION

"The compliance statement for devices supporting frame preemption."

Support of the objects defined in this MIB module also requires support of the IEEE8021-BRIDGE-MIB; the provisions of 17.3.2 apply to implementations claiming support of this MIB. "